

Claims: Cancel all claims of record and substitute new Claims 55 to 81 as follows:

2855. (currently amended) A luminaire suitable for connection to and being powered from a high-frequency power source;
the luminaire having a ~~ballasted-socket~~ballasted socket assembly;
said ~~ballasted-socket~~ballasted socket assembly having a high-frequency input terminal #1, a high-frequency input terminal #2, a ballasting circuit, a lamp socket, interconnecting wiring, and an enclosure;
said enclosure completely enclosing the ballasting circuit, and the interconnecting wiring;
said ~~ballasted-socket~~ballasted socket assembly also provided with a channel;
the high-frequency input terminals being located within said channel;
the channel being of such a design as to receive and connect to a high-frequency cord comprising two parallel conductors encased within and separated from each other by a common insulating sheath;
the high-frequency input terminal #1 making connection to one of the two parallel conductors;
the high-frequency input terminal #2 making connection to the second of the two parallel conductors.

2956. (currently amended) The ~~ballasted-socket~~ballasted socket assembly described in claim 2855, wherein said ~~ballasted-socket~~ballasted socket assembly is provided with a base for mounting;
said base having a recessed channel;
said recessed channel being accessible after the ~~ballasted-socket~~ballasted socket assembly is mounted in place; and
said ~~ballasted-socket~~ballasted socket assembly being adapted to be mounted in place prior to being connected to the high-frequency output cord.

3057. (currently amended) The luminaire described in claim 2855, wherein said ~~ballasted-socket~~ballasted socket assembly is provided with a mounting base;
said mounting base having a recessed channel;
said recessed channel adapted for receiving the high-frequency output cord; and

said ~~ballasted-socket~~ballasted socket assembly being adapted to be mounted in place after receiving the high-frequency output cord.

3458. (currently amended) The luminaire described in claim 2855, wherein the ~~ballasted-socket~~ballasted socket assembly is provided with a socket capable of receiving and supporting a ~~long~~-single-ended lamp having an overall length greater than 6 inches and less than 25 inches;

said luminaire requiring a support bracket to properly support the said long-single-ended lamp; said support bracket being provided as an integral part of the ~~ballasted-socket~~ballasted socket assembly.

3259. (currently amended) The luminaire described in claim 2855, wherein the ~~ballasted-socket~~ballasted socket assembly includes two lamp sockets;

the lamp sockets each having a receptacle capable of receiving a single-ended lamp; said single-ended lamp being a gas-discharge lamp; said receptacles facing opposing directions and located on substantially the same axis.

3360. (currently amended) The luminaire described in claim 2855, wherein the ~~ballasted-socket~~ballasted socket assembly is adapted to power a ~~compact~~-single-ended fluorescent lamp.

3461. (currently amended) The luminaire described in claim 2855, wherein the ~~ballasted-socket~~ballasted socket assembly is provided with a socket capable of receiving and supporting a ~~long~~-single-ended lamp having an overall length greater than 6 inches and less than 25 inches;

said luminaire requiring a support bracket to properly support ~~the long~~said single-ended lamp; said support bracket being provided as a separate piece; said support bracket mounted to the bottom of the shelf or cabinet at the time of installation at a point along the length of the long single-ended lamp; said support bracket being provided with a recess capable of allowing said interconnecting cord to pass through.

4262. (currently amended) A method of providing under-cabinet lighting, comprising the steps of:

- a. mounting one or more ballasted socket ~~ballasted socket~~ assemblies to the under side of a cabinet or a shelf,
- b. passing a high-frequency output cord through each ballasted socket ~~ballasted socket~~ assemblies' recessed channel,
- c. positioning a slide-on cover such that the cover tabs of the slide-on cover engage with a set of base tabs,
- d. sliding the slide-on cover forward,
- e. forcing the high-frequency input terminals to pierce the insulation of the high-frequency output cord and make electrical contact with an internal conductor.

4263. (currently amended) The process described in claim 4262, additionally characterized by including the step of inserting a gas-discharge lamp into the ballasted socket ~~ballasted socket~~ assembly.

4464. (currently amended) The process described in claim 4262, additionally characterized by including the step of inserting a compact single-ended fluorescent lamp into the ballasted socket ~~ballasted socket~~ assembly.

4565. (currently amended) The process described in claim 4262, whereby the ballasted socket ~~ballasted socket~~ assembly includes a socket with an opening suitable for receiving a gas-discharge lamp;

the opening positioned on the ballasted socket ~~ballasted socket~~ assembly such that when the ballasted socket ~~ballasted socket~~ assembly is mounted beneath a cabinet or shelf the opening is facing in a downward position.

4666. (currently amended) The process described in claim 4262, whereby the ballasted socket ~~ballasted socket~~ assembly includes a socket with an opening suitable for receiving a gas-discharge lamp;

the opening positioned on the ~~ballasted socket~~ ~~ballasted-socket~~ assembly such that when the ~~ballasted socket~~ ~~ballasted-socket~~ assembly is mounted beneath a cabinet or shelf the opening is facing to a side.

4767. (currently amended) The process described in claim 4262, whereby the ~~ballasted socket~~ ~~ballasted-socket~~ assembly includes two sockets each having an opening suitable for receiving a gas-discharge lamp;

the opening positioned on the ~~ballasted socket~~ ~~ballasted-socket~~ assembly such that when the ~~ballasted socket~~ ~~ballasted-socket~~ assembly is mounted beneath a cabinet or shelf, the openings are facing opposite sides and neither socket is facing in a downward direction.

5468. (currently amended) A method of providing lighting system, comprising the steps of:

- a. mounting one or more ~~ballasted socket~~ ~~ballasted-socket~~ assemblies,
- b. passing a high-frequency output cord through the recessed channel of each ~~ballasted socket~~ ~~ballasted-socket~~ assembly,
- c. actuating a mechanism that will force the conductors of a high-frequency output cord to make electrical contact with the input terminals of the ~~ballasted socket~~ ~~ballasted-socket~~ assembly,
- d. inserting a gas-discharge lamp into the ~~ballasted socket~~ ~~ballasted-socket~~ assembly.

3769. (currently amended) A ballasted socket assembly for installation under a cabinet or shelf, said ballasted socket assembly including a pair of high-frequency input terminals, a high-frequency ballasting circuit, a lamp socket for a single-ended lamp, interconnecting wiring between the high-frequency input terminals and the high-frequency ballasting circuit, interconnecting wiring between the high-frequency ballasting circuit and the lamp socket for a single-ended lamp, and an enclosure; said enclosure completely enclosing the high-frequency ballasting circuitry, the interconnecting wiring between the high-frequency input terminals and the high-frequency ballasting circuit, and the interconnecting wiring between the high-frequency ballasting circuit and the lamp socket for a single-ended lamp; the term high-frequency referring to a frequency greater than 10 kilohertz;

said enclosure not enclosing a single-ended lamp;

~~The ballasted socket assembly described in claim 35, wherein an optional reflector is being used~~
with the ballasted socket assembly;
said reflector being installed between the ~~ballasted socket~~ballasted socket assembly and the
underside of the cabinet or shelf; and
a lamp being inserted into the ~~ballasted socket~~ballasted socket assembly whereby said lamp and
said ballasted socket assembly are located on the same side of the reflector.

2970. (currently amended) An arrangement comprising: a pair of input terminals, a ballasting
circuit, a socket with output terminals that is capable of receiving, supporting and making
electrical connection to a single-ended lamp, interconnecting wiring between the input
terminals and the ballasting circuitry, interconnecting wiring between the ballasting
circuitry and the output terminals of the socket and an enclosure;

the input to the ballasting circuit being connected to the pair of input terminals;
the output of the ballasting circuit being connected to the output terminals within the socket;
the ballasting circuit being capable of properly igniting and powering a gas discharge lamp when
provided with a high-frequency voltage on the pair of input terminals;
the enclosure completely encapsulating the ballasting circuitry, the interconnecting wiring
between the input terminals and the ballasting circuitry, the interconnecting wiring
between the ballasting circuitry and the output terminals of the socket, and the portion of
the output terminals to which the ballasting circuitry connects;

said enclosure not enclosing a single-ended lamp;

~~The arrangement described in 38, wherein the said pair of input terminals makes connection to a~~
source of high-frequency voltage by way of an insulation-displacement connector;
an insulation-displacement connector being a connector capable of making an insulation-
displacement type connection; and
said arrangement being further characterized in that the arrangement is provided with a single
insulation-displacement connector.

4071. (currently amended) An arrangement comprising: a pair of input terminals, a ballasting
circuit, a socket with output terminals that is capable of receiving, supporting and making

electrical connection to a single-ended lamp, interconnecting wiring between the input terminals and the ballasting circuitry, interconnecting wiring between the ballasting circuitry and the output terminals of the socket and an enclosure;
the input to the ballasting circuit being connected to the pair of input terminals;
the output of the ballasting circuit being connected to the output terminals within the socket;
the ballasting circuit being capable of properly igniting and powering a gas discharge lamp when provided with a high-frequency voltage on the pair of input terminals;
the enclosure completely encapsulating the ballasting circuitry, the interconnecting wiring between the input terminals and the ballasting circuitry, the interconnecting wiring between the ballasting circuitry and the output terminals of the socket, and the portion of the output terminals to which the ballasting circuitry connects;
said enclosure not enclosing a single-ended lamp;
The arrangement described in 38 wherein the said arrangement is being provided with a mounting base;
said mounting base including two recessed channels oriented at right angles with respect to each other;
said mounting base also including two high-frequency input terminals positioned at the intersection of the two channels;
said high-frequency input terminals being suitable for making an insulation displacement connection to a high-frequency output cord; and
the arrangement being designed so that the mounting base will make proper connection to the high-frequency output cord in any one of four possible orientations.

§272. (currently amended) A method of providing under-cabinet lighting, comprising the steps of: passing a high-frequency output cord along the bottom of a cabinet or a shelf,
placing a ballasted socket assembly over the high-frequency output cord,
mounting the ballasted socket assemblies to the under side of the cabinet or shelf;
The process described in claim 48, whereby the ballasted socket assembly includes including a socket with an opening suitable for receiving a gas-discharge lamp; and

the opening positioned on the ~~ballasted-socket~~ballasted socket assembly such that when the ballasted socket assembly is mounted beneath a cabinet or shelf the opening is facing to a side.

5373. (currently amended) A method of providing under-cabinet lighting, comprising the steps of;

passing a high-frequency output cord along the bottom of a cabinet or a shelf;

placing a ballasted socket assembly over the high-frequency output cord;

mounting the ballasted socket assemblies to the under side of the cabinet or shelf;

The process described in claim 43, whereby the ~~ballasted-socket~~ballasted socket assembly includes ~~including~~ two sockets each having an opening suitable for receiving a gas-discharge lamp; and

the opening positioned on the ~~ballasted-socket~~ballasted socket assembly such that when the ~~ballasted-socket~~ballasted socket assembly is mounted beneath a cabinet or shelf, the openings are facing opposite sides and neither socket is facing in a downward direction.

3574. (currently amended) A ~~ballasted-socket~~ballasted socket assembly for installation under a cabinet or shelf;

said ~~ballasted-socket~~ballasted socket assembly including a pair of high-frequency input terminals, a high-frequency ballasting circuit, a lamp socket for a single-ended lamp, interconnecting wiring between the high-frequency input terminals and the high-frequency ballasting circuit, interconnecting wiring between the high-frequency ballasting circuit and the lamp socket for a single-ended lamp, and an enclosure;

said high-frequency input terminals being provided with a high-frequency current;

said high-frequency current having a frequency greater than 10,000 Hertz;

said enclosure completely enclosing the high-frequency ballasting circuitry, the interconnecting wiring between the high-frequency input terminals and the high-frequency ballasting circuit, and the interconnecting wiring between the high-frequency ballasting circuit and the lamp socket for a single-ended lamp; and

said enclosure not enclosing a single-ended lamp.

3675. (currently amended) The ~~ballasted socket~~ballasted socket assembly described in claim 35
74 wherein, said enclosure also includes a mounting base;
said ballasted socket assembly also provided with a channel;
the high-frequency input terminals being located within said channel;
said mounting base having holes capable of receiving screws whereby the ~~ballasted-~~
~~socket~~ballasted socket assembly is mounted directly to the underside of a cabinet or shelf.

3876. (currently amended) An arrangement comprising: a pair of input terminals, a ballasting
circuit, a socket with output terminals that is capable of receiving, supporting and making
electrical connection to a single-ended lamp, interconnecting wiring between the input
terminals and the ballasting circuitry, interconnecting wiring between the ballasting
circuitry and the output terminals of the socket and an enclosure;
the input to the ballasting circuit being connected to the pair of input terminals;
the output of the ballasting circuit being connected to the output terminals within the socket;
the ballasting circuit being capable of properly igniting and powering a gas discharge lamp when
provided with a high-frequency voltage on the pair of input terminals;
said ballasted socket assembly also provided with a channel;
input terminals being located within said channel;
the enclosure completely encapsulating the ballasting circuitry, the interconnecting wiring
between the input terminals and the ballasting circuitry, the interconnecting wiring
between the ballasting circuitry and the output terminals of the socket, and the portion of
the output terminals to which the ballasting circuitry connects; and
said enclosure not enclosing a single-ended lamp.

4177. (currently amended) A high-frequency under-cabinet lighting system comprising: a high-
frequency power source, an interconnecting cable, and multiple luminaires;
the high-frequency power source being connected to and powered from a standard utility power
line and having a high-frequency power output;
the interconnecting cable being connected to said high-frequency power output;
said interconnecting cable not being a track of a track lighting system;

the interconnecting cable being supplied from a manufacturing facility with no luminaires connected thereto; and
the system further characterized in that the system is installed by an installer; during installation, luminaires are connected to a single interconnecting cable at multiple points along the interconnecting cable using an insulation-displacement connection; and the locations of the luminaires being determined by the installer.

4878. (currently amended) A method of providing under-cabinet lighting, comprising the steps of:
passing a high-frequency output cord along the bottom of a cabinet or a shelf,
placing a ~~ballasted-socket~~ballasted socket assembly over the high-frequency output cord,
positioning a channel provided in the ballasted socket assembly directly over the high-frequency output cord,
mounting the ~~ballasted-socket~~ballasted socket assemblies to the under side of the cabinet or shelf.

4979. (currently amended) The process described in claim 4878, additionally characterized by including the step of ~~inserting a gas-discharge lamp into~~positioning a reflector between the ballasted-socketballasted socket assembly and the bottom of the cabinet or shelf.

5080. (currently amended) The process described in claim 4878, additionally characterized by including the step of ~~inserting a compact fluorescent lamp into~~orienting the ballasted-socketballasted socket assembly in one of four possible orientations.

5181. (currently amended) The process described in claim 4878, additionally characterized by including the step of piercing the insulation of the high-frequency output cord with an insulation displacement connector, whereby the ballasted-socket assembly includes a socket with an opening suitable for receiving a gas-discharge lamp;
the opening positioned on the ballasted-socket assembly such that when the ballasted-socket assembly is mounted beneath a cabinet or shelf the opening is facing in a downward position.